

IMPLANTABLE WIRELESS SENSOR FOR PRESSURE MEASUREMENT WITHIN THE HEART

FIELD OF THE INVENTION

This invention relates to chronically implanted sensors for wirelessly sensing
5 pressure, temperature and other physical properties within the human body. More
particularly, the invention concerns a wireless, un-powered micromachined pressure sensor
that can be delivered using endovascular techniques to the interior of the human heart.

BACKGROUND OF THE INVENTION

10 The measurement of blood pressure within the human heart provides critical
information regarding the organ's function. Many methods and techniques have been
developed to give physicians with the ability to monitor heart function to properly diagnose
and treat various diseases and medical conditions. For example, a sensor or transducer
placed within the chambers of the heart can be used to record variations in blood pressure
based on physical changes to a mechanical element within the sensor. This information is
15 then transferred from the sensor to external device that is capable of translating the data from
the sensor into a measurable value that can be displayed. The drawback of this type of
sensor is that there must be a physical connection between the sensor and the external device,
thus limiting its use to acute settings.

20 Many types of wireless sensors have been proposed that would allow implantation of
the device into the body and then through the appropriate coupling means, pressure reading
can be made over longer periods of interest. The primary limitation to these type of sensors
are the fabrication methods used to manufacture them do not provide sufficient
miniaturization to allow them to be introduced and implanted into the heart using non-
surgical, catheter based techniques.

25 For a sensor that is designated to be placed within the heart, additional considerations
are required. A feature must be provided that will allow the sensor to be permanently

secured to the wall of the heart in a manner that will exclude any possibility of movement of the sensor or displacement out of the heart. Finally, an implantable sensor of this type must be assembled using the materials and fabrications methods that ensure appropriate biocompatibility and long term mechanical and electrical durability.

3-12-03
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
222

Patent No. 6,113,553 is a representative example. The Chubbuck patent demonstrates how a combination of a pressure sensitive capacitor placed in series with an inductor coil provides the basis of a wireless, un-powered pressure sensor that is suitable for implantation into the human body. Construction of an LC circuit in which variations of resonant frequency
5 correlate to changes in measured pressure and which these variations can be detected remotely through the use of electromagnetic coupling are further described in Allen et al., U.S. Patent No. 6,111,520, incorporated herein by reference.

The device embodied by the Chubbuck patent is manufactured using conventional techniques, thus requiring surgical implantation and thus limiting its applicability to areas
10 that are easily accessible to surgery (i.e., skull).

Thus, the need exists for a biocompatible, wireless, un-powered pressure sensor that for the purposes of introduction and delivery within the human heart can be manipulated into a smaller shape and size by rolling or folding it into a cylindrical form and loaded into a small diameter catheter. Then upon positioning the catheter within the desired chamber of
15 the heart, the sensor can be deployed and through the use super-elastic alloy components in the form of anchors or hooks secured to the interior wall of the heart.

OBJECTS OF THE INVENTION

It is an object of this invention to provide an implantable wireless sensor.

It is also an object of this invention to provide a wireless, unpowered micromechanical, flexible sensor that can be delivered endovascularly to a heart chamber.

5 It is a further object of this invention to provide an implantable, wireless, unpowered sensor that can be delivered endovascularly to a heart chamber to measure pressure and/or temperature.

These and other objects of the invention will become more apparent from the discussion below.

SUMMARY OF THE INVENTION

10 The present invention describes a sensor that can be fabricated using micro-machining techniques and can be implanted into the human body using non-surgical methods for the measurement of physical parameters. This sensor is fabricated using MicroElectroMechanical Systems (MEMS) technology, which allows the creation of a
15 flexible device that is small, accurate, precise, durable, robust, biocompatible, radiopaque and insensitive to changes in body chemistry, biology or external pressure. This device will not require the use of wires to relay pressure information externally nor need an internal power supply to perform its function.

20 The MEMS approach to sensor design lends itself to the fabrication of small, flat sensors that can be formed using biocompatible polymers as substrate materials. The pressure sensor described above can then be manipulated into a smaller shape and size by rolling, bending, or folding it into a cylindrical form. This smaller object can then be introduced into the chambers of the human heart using endovascular catheter techniques. Once positioned within the heart, the device unfurls into a preferred flat shape. Super-elastic
25 alloy components may be incorporated into the device such as hooks, anchors, harpoons or

coils are designed to secure the pressure sensor to the wall of the heart and resist displacement due to movement of the heart wall or from the interaction of blood being pumped through the heart. In addition, appropriately biocompatible coatings may be applied to the surface of the sensor in order to prevent adhesion of biological substances to the sensor that could interfere with its proper function.

The pressure sensor can be manufactured using Micro-machining techniques that were developed for the integrated circuit industry. An example of this type of sensor features an inductive-capacitive (LC) resonant circuit with a variable capacitor and is described in Allen et al., U.S. Patent No. 6,111,520 incorporated herein by reference. In this sensor, the capacitance varies with the pressure of the environment in which the capacitor is placed. Consequently, the resonant frequency of the LC circuit of the pressure sensor varies depending on the pressure of the environment. The pressure sensor is made of completely passive components having no active circuitry or power sources such as batteries. The pressure sensor is completely self-contained having no leads to connect to an external circuit or power source. Furthermore, these same manufacturing techniques can be used to add additional sensing capabilities, such as the ability to measure temperature by the addition of a resistor to the basic LC circuit.

When introduced into heart, the pressure sensor can provide pressure related data by use of an external measuring device. As disclosed in the Allen et al. patent, several different excitation systems can be used. For example, the sensor can be electromagnetically coupled to a transmitting antenna. Consequently, a current is induced in the sensors, which oscillates at the resonant frequency of the sensor. This oscillation causes a change in the frequency spectrum of the transmitted signal. From this change, the bandwidth and resonant frequency of the particular sensor may be determined, from which the corresponding change in pressure can be calculated.

Accordingly, the present invention provides for an impedance system and method of determining the resonant frequency and bandwidth of a resonant circuit within a particular

sensor. The system includes a transmitting antenna, which is coupled to an impedance analyzer. The impedance analyzer applies a constant voltage signal to the transmitting antenna scanning the frequency across a predetermined spectrum. The current passing through the transmitting antenna experiences a peak at the resonant frequency of the sensor.

5 The resonant frequency and bandwidth are thus determined from this peak in the current.

The method of determining the resonant frequency and bandwidth using an impedance approach may include the steps of transmitting an excitation signal using a transmitting antenna and electromagnetically coupling a sensor having a resonant circuit to the transmitting antenna thereby modifying the impedance of the transmitting antenna. Next,
10 the step of measuring the change in impedance of the transmitting antenna is performed, and finally, the resonant frequency and bandwidth of the sensor circuit are determined.

In addition, the present invention provides for a transmit and receive system and method for determining the resonant frequency and bandwidth of a resonant circuit within a particular sensor. According to this method, an excitation signal of white noise or
15 predetermined multiple frequencies is transmitted from a transmitting antenna, the sensor being electromagnetically coupled to the transmitting antenna. A current is induced in the resonant circuit of the sensor as it absorbs energy from the transmitted excitation signal, the current oscillating at the resonant frequency of the resonant circuit. A receiving antenna, also electromagnetically coupled to the transmitting antenna, receives the excitation signal minus
20 the energy which was absorbed by the sensor. Thus, the power of the received signal experiences a dip or notch at the resonant frequency of the sensor. The resonant frequency and bandwidth are determined from this notch in the power.

The transmit and receive method of determining the resonant frequency and bandwidth of a sensor circuit includes the steps of transmitting a multiple frequency signal
25 from transmitting antenna, and, electromagnetically coupling a resonant circuit on a sensor to the transmitting antenna thereby inducing a current in the sensor circuit. Next, the step of receiving a modified transmitted signal due to the induction of current in the sensor circuit is

performed. Finally, the step of determining the resonant frequency and bandwidth from the received signal is executed.

Yet another system and method for determining the resonant frequency and bandwidth of a resonant circuit within a particular sensor includes a chirp interrogation system. This system provides for a transmitting antenna which is electromagnetically coupled to the resonant circuit of the sensor. An excitation signal of white noise or predetermined multiple frequencies is applied to the transmitting antenna for a predetermined period of time, thereby inducing a current in the resonant circuit of the sensor at the resonant frequency. The system then listens for a return signal which radiates from the sensor. The resonant frequency and bandwidth of the resonant circuit are determined from the return signal.

The chirp interrogation method for determining the resonant frequency and bandwidth of a resonant circuit within a particular sensor includes the steps of transmitting a multi-frequency signal pulse from a transmitting antenna, electromagnetically coupling a resonant circuit on a sensor to the transmitting antenna thereby inducing a current in the sensor circuit, listening for and receiving a return signal radiated from the sensor circuit, and determining the resonant frequency and bandwidth from the return signal.

In addition, the present invention provides an analog system and method for determining the resonant frequency of a resonant circuit within a particular sensor. The analog system comprises a transmitting antenna coupled as part of a tank circuit which in turn is coupled to an oscillator. A signal is generated which oscillates at a frequency determined by the electrical characteristics of the tank circuit. The frequency of this signal is further modified by the electromagnetic coupling of the resonant circuit of a sensor. This signal is applied to a frequency discriminator which in turn provides a signal from which the resonant frequency of the sensor circuit is determined.

The analog method for determining the resonant frequency and bandwidth of a resonant circuit within a particular sensor includes the steps of generating a transmission

signal using a tank circuit which includes a transmitting antenna, modifying the frequency of the transmission signal by electromagnetically coupling the resonant circuit of a sensor to the transmitting antenna, and converting the modified transmission signal into a standard signal for further application.

5 The above methods lend themselves to the creation of small and simple to manufacture hand-held electronic devices that can be used without complication.

Other features and advantages of the present invention will become apparent to one with skill in the art upon examination of the following drawings and detailed description. It is intended that all such additional features and advantages be included herein within the scope
10 of the present invention, as defined by the claims.

Thus, this patent discloses a simple method of monitoring the pressure within the human heart by inserting a pressure transducer using a catheter and using a small, hand-held read device to measure the pressure easily, safely, inexpensively and accurately. It also includes a method of introducing the sensor into the body by using the steps of folding or
15 rolling the sensor into a cylinder, loading it into a catheter and deploying into the heart by allowing it to unroll or unfold, either by itself or facilitated by the incorporation of a super-elastic alloy component. The same super-elastic element also provides the means to permanently securing the device to the interior of the heart.

Delivery of the device of the invention to a heart chamber may be accomplished as
20 follows: Using the standard Seldinger technique, the physician gains access to the patient's jugular artery and places a vessel introducer with a hemostatic valve. Under direct fluoroscopic visualization, a flexible guidewire is inserted through the introducer catheter and maneuvered such that its tip is stationed within a chamber of the heart. In a preferred delivery system a catheter has a "daisy shape" sensor folded into its distal end, so that the
25 middle, flat section of the sensor is essentially normal to the longitudinal axis of the catheter. A solid or hollow cylindrical rod or member is pushed distally to push the sensor from the

distal end of the catheter and, optionally, to attach to an inner wall of the heart chamber with an anchor member.

Optionally, a coaxial delivery catheter consisting of two hollow extruded polymeric catheters, the smaller of the two disposed inside the larger one, is inserted over the guidewire and through the introducer and advanced distally until its tip is within the heart chamber. The smaller catheter has an annular space to hold a folded sensor, which is released when the outer catheter is withdrawn proximally.

In a preferred delivery procedure, a sensor is attached to a small diameter, proximally extending "safety" or tether wire. The sensor and safety wire are also positioned in a lumen in a catheter or in the annular space between two coaxial catheters, but the safety wire runs the entire length of the delivery catheter and extends proximally past the proximal end of that catheter outside the patient. In this configuration, the sensor remains secured to the tether wire after the coaxial delivery catheter is removed from the patient. The sensor is detached from the tether wire using any of the methods known in the art, and the wire is removed.

In a further alternative delivery procedure the sensor can be loaded into the annular space between the inner and outer catheters by inserting the sensor into a longitudinal slit cut into the outer catheter and attaching a tab on the sensor's surface into a slot cut into the inner coaxial catheter. By rotation of the inner tube, the sensor will be retracted through the slit and positioned in the annular space between the two tubes. To deploy the device, the rotation of the inner tube is reversed and the sensor emerges through the slit of the outer catheter. There are two specific advantages to this deployment mechanism. First, the sensor can be packaged and stored in a flat configuration. This is desirable since long term storage in a pre-loaded curved geometry could make it more difficult for the sensor to re-establish the flat arrangement that is optimal for effective electro-magnetic inductive coupling with the external read-out unit. The second advantage is that by cutting the longitudinal slit at angle

that is offset from the main axis of the outer tube, the sensor will be biased into a planar configuration as it is forced through the slit during the deployment process.

A safety wire system can also be used with this mechanism, although the wire may be external to the outer coaxial tube. As described above, the wire will remain attached to the sensor during the deployment process and will stay within the heart chamber while the delivery catheter is removed. Subsequent to insertion and deployment of the stent-graft, the wire will be detached from the sensor and pulled out of the body.

The detachment of the wire from the sensor can be accomplished in several ways. The wire may be simply glued to the sensor using an adhesive. To separate the sensor from the wire, a thin-walled, metal or polymer tube is passed along the length of the wire and positioned at the adhesive joint. While holding this tube steady, the wire is then retracted into the tube. Sufficient traction can be applied to the segment of the wire that remains outside of the body to cause the adhesive to joint to fail and allow removal of the wire.

An alternative method would rely on a mechanical connection between the wire and sensor such as adding threads to the end of the wire which could then be connected to a matching threaded female receptacle on the sensor. To separate the wire from the sensor, counter-rotation would be applied to the wire until the threads disengage. One could envision many variations of this design that would involve the mechanical locking and un-locking of two mating components.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a front view of an embodiment of the invention;

Fig. 2 is a lateral view of the embodiment of the invention shown in Fig. 1;

Fig. 3 is a lateral view of an embodiment of the invention of Fig. 1 folded for
5 delivery;

Fig. 4 is a front view of another embodiment of the invention;

Fig. 5 is a lateral view of a yet further embodiment of the invention;

Figs. 6 and 7 are each a lateral view of an embodiment of the invention with an
anchoring mechanism;

10 Fig. 8 is an exploded schematic representation of construction of one embodiment of
a sensor;

Fig. 9 is a schematic representation of an embodiment of the invention with
distributed capacitance;

15 Figs. 10 and 11 are each a schematic, partial cross-sectional view of an embodiment
of a sensor according to the invention;

Fig. 12 is a schematic representation of an alternate shape for an embodiment of the
invention;

Fig. 13 is a cross-sectional view of the distal end of a delivery catheter with the
embodiment shown in Fig. 12;

20 Fig. 14 is a schematic of another sensor according to the invention;

Fig. 15 is a drawing of a read-out device employed according to the invention; and

Fig. 16 is a block diagram of an electrical circuit useful according to the invention.

DETAILED DESCRIPTION OF THE INVENTION

The invention can perhaps be better understood by referring to the drawings. One embodiment of a sensor according to the invention is shown in Figures 1, 2, and 3, where a disc-shaped sensor 10 comprises a capacitor disk 12 and a wire spiral 14. Figure 2 is a lateral view of sensor 10, and Figure 3 is a lateral view of sensor 10 in a folded configuration for insertion. The fact that sensor 10 is sufficiently flexible to be folded as shown in Figure 4 is an important aspect of the invention.

In Figure 4 a ring 20 comprised of a shape memory alloy such as nitinol has been attached to, for example, with adhesive, or incorporated into, for example, layered within, a sensor 22.

Figure 5 is a lateral cross-sectional view of a circular sensor 30 having a ring 32 comprised of a shape memory alloy such as nitinol encompassing the outer edge 34 of sensor 30. Ring 32 preferably is attached to outer edge 34 by a suitable physiologically acceptable adhesive 36, such as an appropriate epoxy or cyanoacrylate material. Preferably the ring will be radiopaque.

The size of the circular sensors of the invention will vary according to factors such as the intended application, the delivery system, etc. The circular sensors are intended to be from about 0.5 to about 3 cm in diameter, with a thickness of from about 0.05 to about 0.30 in. When a ring 32 is employed, the thickness of the ring, i.e., the width of the outside surface 38, will preferably be from about 1.5 to about 3.5 times the thickness of the sensor.

Figures 6 and 7 each represent a lateral view of a sensor with an anchoring member. In Figure 6 sensor 40 has a screw/coil 42, and in Figure 7 sensor 40 has an anchor 44 with umbrella-like projections 46. When pressure is applied to the flat side 48 of sensor 40, anchor 42 or 44 will penetrate a vessel wall, organ wall, or other substrate to cause sensor 36 to remain in a desired position or location. Alternatively, an anchoring mechanism such as is shown in Figures 6 and 7 could be attached to ring 32 in Figure 5.

The pressure sensor of the invention can be manufactured using Micro-machining techniques that were developed for the integrated circuit industry. An example of this type of sensor features an inductive-capacitive (LC) resonant circuit with a variable capacitor, as is described in Allen et al., U.S. Patent No. 6,111,520, all of which is incorporated herein by reference. The sensor contains two types of passive electrical components, namely, an inductor and a capacitor. The sensor is constructed so that the fluid pressure at the sensor's surface changes the distance between the capacitor's parallel plates and causes a variation of the sensor's capacitance.

In a preferred embodiment the sensor of the invention is constructed by laminating several layers of material together, as shown, for example, in Figure 8. A first layer 242 is fabricated from a sheet of polyimide film (e.g. KAPTON, available from Du Pont) upon which a micro-machined copper pattern 244 is deposited. Pattern 244 preferably consists of a circular conductive segment in the center of the sheet surrounded by a spiral coil. A second layer 248 comprises a sheet of flexible adhesive through which hole 250 has been cut in the center. (Optionally there may be more than one such layer 248.) A final layer 252 is another sheet of polyimide film with a copper pattern 254 that is a mirror image of pattern 244. When assembled, the first, second, and third layers are aligned such that the holes in the middle adhesive layers are centered between the circular conductive segments in the middle of the two outer polyimide layers 242 and 252. In this way a capacitor (defined as an electric circuit element used to store charge temporarily, consisting in general of two metallic plates separated and insulated from each other by a dielectric) is formed. At the same time, the two metal spirals on the polyimide sheets 242 and 252 form an inductor component of a miniature electrical circuit.

The sensor exhibits the electrical characteristics associated with a standard LC circuit. An LC circuit is simply a closed loop with only two elements, a capacitor and an inductor. If a current is induced in the LC loop, the energy in the circuit is shared back and forth between the inductor and capacitor. The result is an energy oscillation that will vary at a specific

frequency. This is termed the resonant frequency of the circuit and it can be easily calculated as its value is dependent on the circuit's inductance and capacitance. Therefore, a change in capacitance will cause the frequency to shift higher or lower in linear proportion to the change in the value of capacitance.

5 As noted above, the capacitor in the assembled pressure sensor consists of the two circular conductive segments separated by an air gap. If a pressure force is exerted on these segments it will act to deform the outer polyimide sheet and move the two conductive segments closer together. This will have the effect of reducing the air gap between them which will consequently change the capacitance of the circuit. The result will be a shift in the
10 circuit's resonant frequency that will be in direct proportion to the force applied to the sensor's surface.

Because of the presence of the inductor, it is possible to electromagnetically couple to the sensor and induce a current in the circuit. This allows for wireless communication with the sensor and the ability to operate it without the need for an internal source of energy such
15 as a battery. Thus, if the sensor is located within the chamber of the heart, it will be possible to determine the pressure within the chamber in a simple, non-invasive procedure by remotely interrogating the sensor, recording the resonant frequency and converting this value to a pressure measurement. The readout device generates electromagnetic energy that penetrates through the body's tissues to the sensor's implanted location. The sensor's
20 electrical components absorb a fraction of the electromagnetic energy that is generated by the readout device via inductive coupling. This coupling induces a current in the sensor's circuit that oscillates at the same frequency as the applied electromagnetic energy. Due to the nature of the sensor's electro-mechanical system there exists a frequency of alternating current at which the absorption of energy from the readout device is at a minimum. This frequency is a
25 function of the capacitance of the device. Therefore, if the sensor's capacitance changes, so will the frequency at which it minimally absorbs energy from the readout device. Since the sensor's capacitance is mechanically linked to the fluid pressure at the sensor's surface, a measurement of this frequency by the readout device gives a relative measurement of the

10054672-012202

3-22-03

fluid pressure. If calibration of the device is performed, then an absolute measurement of pressure can be made. See, for example, the extensive discussion in the Allen et al. patent, again incorporated herein by reference, as well as Gershenfeld et al., U.S. Patent No. 6,025,725, incorporated herein by reference.

5 The pressure sensor is made of completely passive components having no active circuitry or power sources such as batteries. The pressure sensor is completely self-contained having no leads to connect to an external circuit or power source. Furthermore, these same manufacturing techniques can be used to add additional sensing capabilities, such as the ability to measure temperature by the addition of a resistor to the basic LC circuit.

10 Several alternative configurations of the LC circuit design can be considered to address specific biological and manufacturing issues. For example, in one embodiment of the sensor the capacitor element consists of two plates that are separated by a suitable dielectric material, such as air, inert gas, fluid or a vacuum. To ensure the long term integrity of the sensor, various coatings could be applied to the surface or between the polymeric layers used to form the sensor. These coating can be used to provide a hermetic seal that will prevent leakage of body fluids into the cavity or permeation of the cavity material (gas, vacuum or fluid) out of the sensor. In an another embodiment of the invention, shown in Figure 9, a sensor 270 has a multitude of capacitors 275 formed either as separate elements or as an array. In such a distributed capacitance configuration, there can be a more accurate and more sensitive measurement of pressure.

It is within the scope of the invention that the frequency response to the sensor will be in the range of from about 1 to about 200 MHz, preferably from about 1 to about 100 MHz, and more preferably from about 2 to about 90 MHz, with a Q factor from about 5 to about 80, preferably from about 10 to about 70, more preferably from about 10 to 60.

25 In a further embodiment of the invention there is no direct electrical connection between the two sides of the LC circuit. Referring again to the sensor described in the Allen et al. patent, the device is constructed using multiple layers upon which the necessary circuit

elements. Disposed on the top and bottom layer are metal patterns constructed using micro-machining techniques which define a top and bottom conductor and a spiral inductor coil. To provide for an electrical contact between the top and bottom layers small vias or holes are cut through the middle layers. When the layers are assembled, a metal paste is forced into the small vias to create direct electrical connections or conduits. However, experimentation has shown that due to parasitic capacitance that is created between the top and bottom inductor coils, a vialess operational LC circuit can be created. This absence of via holes represents a significant improvement to the sensor in that it simplifies the manufacturing process and, more importantly, significantly increases the durability of the sensor making it more appropriate for use inside the human body.

Figure 10 is a partial cross-sectional review of the sensor shown in Figure 8, where first layer 242, second layer 248, and third layer 252 are sandwiched together. A cylindrical space 256 comprises a pressure sensitive capacitor. No via holes are present. The sensor 278 shown in Figure 11 comprises a first polyimide layer 280, a second, adhesive layer 282, and a third, polyimide layer 284. First layer 280 has a copper pattern comprising a coil 286 and a disk 288, and third layer 284 comprises a coil 290 and a disk 292. A cylindrical space 296 comprises a pressure sensitive capacitor. A diode 294 connected between coils 286 and 290 creates a non-linear sensor, i.e., a sensor where the frequency change is non-linear as compared to a change in pressure.

The design of the sensor is not limited to a specific geometric configuration. In the specific example noted above the inductor component is described as a spiral coil. Other embodiments of the sensor could utilize oval, rectangular or an amorphous shape. Specific electrical, mechanical and biologic advantages could be obtained by employing these various geometric designs. By way of example, a rectangular shaped sensor in which the ratio of length to width was greater than four would greater lend itself to catheter based delivery as is would minimize the radius of curvature required to position the folded device within a small diameter catheter. Alternatively, a more elaborate shape, such as one resembling the petals

of a flower, would lend itself to more complex folding patterns that could facilitate delivery to specific areas of a chamber of the heart.

In a preferred embodiment of the invention a foldable sensor is delivered to the chamber of a patient's heart in the distal end of a delivery catheter. The sensor can be regularly or irregularly shaped so that outer portions of the sensor can fold to about a 90° angle as compared to a relatively flat, middle portion of the sensor. For example, in Figure 12, a daisy or flower-shaped sensor 308 has a capacitor surface 310 connected to a wire 312 that partly follows the outer configuration of sensor 308. Petals 314 fold so that sensor 308 with a distal anchor 316 can be "loaded" into a catheter 318, as shown in Figure 13. When the distal end 320 of catheter 318 is in position, a pushing rod member 322 is pushed distally to cause sensor 308 to be released from catheter 318 and attach to the inner surface of the wall of a heart chamber (not shown).

It is especially preferred that rod member 322 will be temporarily affixed to sensor 308 for at least two purposes. First, rod member 322 functions as a safety or tether wire. And second, rod member 322 will be capable of twisting or otherwise maneuvering sensor 308 so that anchor 368 will attach to the heart chamber wall. Once sensor 308 is attached, rod member 322 is disengaged from sensor 308 and withdrawn proximally.

Another embodiment of a sensor is shown in Figure 14, where circular sensor 330 comprises flexible cut-outs 332. The first outer layer 334 comprises a polyimide substrate with a copper pattern comprising a coil 340 and several, from 2 to 6, disks 342 to form pressure sensitive capacitors. Sensor 330 also comprises at least one adhesive layer (not shown) and a third outer layer corresponding to the first outer layer (not shown). Preferably sensor 330 has at least one diode connecting the copper coils of the first and third layers.

The flexible cut-outs ³³²~~352~~ facilitate, among other things, folding of sections of sensor ³³⁰~~370~~ for placement in, or arrangement upon, a delivery catheter, such as in Figure 13. The sections can also be folded to create either a "Z" shape or, for example, a "U" shape, for

other applications. It is within the scope of the invention that variously numbered and shaped cut-outs could be used for particular applications.

While a preferred delivery system is described above, it is within the scope of the invention that other delivery systems could be employed. Other such delivery systems are described in, for example, co-pending, commonly assigned U.S. patent application Serial No. 10/054,671 ~~[24301.10]~~, filed January 22, 2002, incorporated herein by reference.

Further, the invention is not limited to the implantation of a single sensor. Since the biological environment within a patient's heart is not necessarily homogeneous, multiple pressure sensors may be introduced into a patient's heart, each being positioned at different locations. In this situation, each sensor may be designed with a unique signature (obtained by changing the resonant frequency of the sensor), so that the pressure measurement derived from one sensor can be localized to its specific position within the heart.

When introduced into the chamber of a patient's heart, the pressure sensor can provide pressure related data by use of an external measuring device. As disclosed in the Allen et al. patent, several different excitation systems can be used. The readout device generates electromagnetic energy that can penetrate through the body's tissues to the sensor's implanted location. The sensor's electrical components can absorb a fraction of the electromagnetic energy that is generated by the readout device via inductive coupling. This coupling will induce a current in the sensor's circuit that will oscillate at the same frequency as the applied electromagnetic energy. Due to the nature of the sensor's electro-mechanical system there will exist a frequency of alternating current at which the absorption of energy from the readout device is at a minimum. This frequency is a function of the capacitance of the device. Therefore, if the sensor's capacitance changes so will the frequency at which it minimally absorbs energy from the readout device. Since the sensor's capacitance is mechanically linked to the fluid pressure at the sensor's surface, a measurement of this frequency by the readout device can give a relative measurement of the fluid pressure. If calibration of the device is performed then an absolute measurement of pressure can be made

The circuitry used to measure and display pressure is contained within a simple to
 operate, battery powered, hand-held electronic unit 400, as shown in Figure 15. This unit
 400 also contains the antenna needed to perform the electromagnetic coupling to the sensor.
 The antenna may be integrated into the housing for the electronics or it may be detachable
 5 from the unit so that it can be positioned on the surface of the body 402 in proximity to the
 implanted sensor and easily moved to optimize the coupling between antenna and sensor.
 The antenna itself may consist of a simple standard coil configuration or may incorporate
 ferrous elements to maximize the coupling efficiency. The electronic device would feature
 an LCD or LED display 404 designed to clearly display the recorded pressure in
 10 physiologically relevant units such as mm HG. In an alternative embodiment, the display
 may be created by integrating a commercially available hand-held computing device such as
 a Palm® or micro-PC into the electronic circuitry and using this device's display unit as the
 visual interface between the equipment and its operator. A further advantage of this
 approach is that the hand-held computer could be detached from the read-out unit and linked
 15 to a standard desktop computer. The information from the device could thus be downloaded
 into any of several commercially available data acquisition software programs for more
 detailed analysis or for electronic transfer via hard media or the internet to a remote location.

Accordingly, the present invention provides for an impedance system and method of
 determining the resonant frequency and bandwidth of a resonant circuit within a particular
 20 sensor. The system includes a transmitting antenna, which is coupled to an impedance
 analyzer. The impedance analyzer applies a constant voltage signal to the transmitting
 antenna scanning the frequency across a predetermined spectrum. The current passing
 through the transmitting antenna experiences a peak at the resonant frequency of the sensor.
 The resonant frequency and bandwidth are thus determined from this peak in the current.

25 The method of determining the resonant frequency and bandwidth using an
 impedance approach may include the steps of transmitting an excitation signal using a
 transmitting antenna and electromagnetically coupling a sensor having a resonant circuit to

the transmitting antenna thereby modifying the impedance of the transmitting antenna. Next, the step of measuring the change in impedance of the transmitting antenna is performed, and finally, the resonant frequency and bandwidth of the sensor circuit are determined.

In addition, the present invention provides for a transmit and receive system and method for determining the resonant frequency and bandwidth of a resonant circuit within a particular sensor. According to this method, an excitation signal of white noise or predetermined multiple frequencies is transmitted from a transmitting antenna, the sensor being electromagnetically coupled to the transmitting antenna. A current is induced in the resonant circuit of the sensor as it absorbs energy from the transmitted excitation signal, the current oscillating at the resonant frequency of the resonant circuit. A receiving antenna, also electromagnetically coupled to the transmitting antenna, receives the excitation signal minus the energy which was absorbed by the sensor. Thus, the power of the received signal experiences a dip or notch at the resonant frequency of the sensor. The resonant frequency and bandwidth are determined from this notch in the power.

The transmit and receive method of determining the resonant frequency and bandwidth of a sensor circuit includes the steps of transmitting a multiple frequency signal from transmitting antenna, and, electromagnetically coupling a resonant circuit on a sensor to the transmitting antenna thereby inducing a current in the sensor circuit. Next, the step of receiving a modified transmitted signal due to the induction of current in the sensor circuit is performed. Finally, the step of determining the resonant frequency and bandwidth from the received signal is executed.

Yet another system and method for determining the resonant frequency and bandwidth of a resonant circuit within a particular sensor includes a chirp interrogation system. This system provides for a transmitting antenna which is electromagnetically coupled to the resonant circuit of the sensor. An excitation signal of white noise or predetermined multiple frequencies is applied to the transmitting antenna for a predetermined period of time, thereby inducing a current in the resonant circuit of the sensor at the resonant

frequency. The system then listens for a return signal which radiates from the sensor. The resonant frequency and bandwidth of the resonant circuit are determined from the return signal.

The chirp interrogation method for determining the resonant frequency and bandwidth of a resonant circuit within a particular sensor includes the steps of transmitting a multi-frequency signal pulse from a transmitting antenna, electromagnetically coupling a resonant circuit on a sensor to the transmitting antenna thereby inducing a current in the sensor circuit, listening for and receiving a return signal radiated from the sensor circuit, and determining the resonant frequency and bandwidth from the return signal.

A representative block diagram of an electrical circuit that can be used to interrogate the sensor and determine the resonant frequency is shown in Figure 16. A transmitter and receiver, i.e., a transceiver 422, has an antenna 424 for generating and receiving signals from a sensor 426. Transceiver 422 is an electronic or digital connection with a phase detector 430, a microprocessor 432, and a frequency synthesizer 434. Microprocessor 432 is in turn connected to an interface 436 such as a terminal. Power supply 438 regulates and provides electrical power to the system.

The present invention also provides an analog system and method for determining the resonant frequency of a resonant circuit within a particular sensor. The analog system comprises a transmitting antenna coupled as part of a tank circuit which in turn is coupled to an oscillator. A signal is generated which oscillates at a frequency determined by the electrical characteristics of the tank circuit. The frequency of this signal is further modified by the electromagnetic coupling of the resonant circuit of a sensor. This signal is applied to a frequency discriminator which in turn provides a signal from which the resonant frequency of the sensor circuit is determined.

The analog method for determining the resonant frequency and bandwidth of a resonant circuit within a particular sensor includes the steps of generating a transmission signal using a tank circuit which includes a transmitting antenna, modifying the frequency of

the transmission signal by electromagnetically coupling the resonant circuit of a sensor to the transmitting antenna, and converting the modified transmission signal into a standard signal for further application.

10 The invention further includes an alternative method of measuring pressure in which a non-linear element such as a diode or polyvinylidenedifluoride piezo-electric polymer is added to the LC circuit. A diode with a low turn-on voltage such as a Schottky diode can be fabricated using micro-machining techniques. The presence of this non-linear element in various configurations within the LC circuit can be used to modulate the incoming signal from the receiving device and produce different harmonics of the original signal. The read-out circuitry can be tuned to receive the particular harmonic frequency that is produced and use this signal to reconstruct the fundamental frequency of the sensor. The advantage of this approach is two-fold; the incoming signal can be transmitted continuously and since the return signal will be at different signals, the return signal can also be received continuously.

15 The above methods lend themselves to the creation of small and simple to manufacture hand-held electronic devices that can be used without complication.

20 One additional concern regarding devices designated for long term implantation in the human body is maintenance of electrical stability over time as the environment the sensor has been placed in changes. Under this scenario the sensor's accuracy may drift from its original baseline. It would thus be desirable to have available to the user of the device, a method for determining if the sensor is functioning properly and also to be able to recalibrate the device anytime after it has been implanted. This invention therefore also includes a method of using acoustic energy to challenge the sensor and determining to what degree (if any) sensor performance has been degraded. In this method, energy in the ultrasound range is directed towards the sensor and a measurement is made of the mechanical resonance of the sensor membrane. This same measurement can be made at point after the sensor has been implanted. By comparing the values of these two measurements a determination of the degree of change in mechanical resonance frequency can be established. This value can then

be used to create a calibration factor that can be applied to the pressure reading taken post-implantation in order to adjust the measured value to reflect the actual pressure within the heart chamber.

The preceding specific embodiments are illustrative of the practice of the invention.

- 5 It is to be understood, however, that other expedients known to those skilled in the art or disclosed herein, may be employed without departing from the spirit of the invention of the scope of the appended claims.

10054679-012202